

PART NUMBER

ESOM2RC10BE

MODEL DESCRIPTION

Socket Outlets Switched 10 Amp 250Va.c. with Residual Current Device (RCD) 230-240Va.c. 20 Amp Type 1 10mA, marked "CLEANING PURPOSES ONLY"



ESOM2RC10BE

TECHNICAL DATA

PART NUMBER	ESOM2RC10BE	MAXIMUM TRIPPING CURRENT	RCD - 10mA
DESCRIPTION	Socket Outlets Switched 10 Amp 250Va.c. with RCD 230-240Va.c. 20 Amp Type 1 10mA, marked "CLEANING PURPOSES ONLY"	RCD TYPE	Type I RCD
ORIENTATION	Horizontal	WITHSTAND RATING	3KA Circuit Protection by MCB or HRC Fuse 20A max
SUPPLY VOLTAGE	RCD - 230-240Va.c. / Socket Outlets - 250Va.c.	COLOUR	Beige (BE) (cleaning purposes only)
FREQUENCY	RCD - 50Hz	MOUNTING CENTRES	84mm
POLES DESCRIPTION	RCD - Double Pole / Socket Outlets - Single Pole	COMPLIANCE	AS/NZS 3190, AS/NZS 3003, AS/NZS 3112, ISO 22196
MAXIMUM CURRENT	RCD - 20A / Socket Outlets - 10A		

esco
industries

THE ESCO GROUP OF COMPANIES

esco industries MASRAP **MediTek**

modempak

ESCO INDUSTRIES

89 Egerton St (Cnr Fariola & Egerton)
 PO Box 6193, Silverwater
 NSW 2128 AUSTRALIA

MODEMPAK NZ

30 Fairfax Ave, Penrose
 AUCKLAND 1642 NEW ZEALAND

T 1300 879 363 F 1300 879 364

customer.service@escoindustries.com.au
 www.escoindustries.com.au

D +64 9 526 1880 **Freecall** 0800 663 367

F +64 9 580 0606
 customer.service@modempak.co.nz
 www.modempak.co.nz